

Aqara Hub E1

USB-A Zigbee 3.0 Smart Home Hub

The Aqara Hub E1 is a compact smart home hub with built-in Zigbee 3.0, USB-A power, 210-degree adjustable connector design, wide ecosystem compatibility and 2.4 GHz Wi-Fi repeater functionality.

Key Features

- **Zigbee 3.0 Hub**
Connects Aqara Zigbee child devices with stable, energy-efficient smart home networking.
- **Powered by USB-A**
Plugs into a USB-A port on a power bank, power strip, outlet, PC, or router.
- **210° Adjustable Shaft**
Flexible USB connector angle makes installation easier in tight spaces.
- **Compact & Portable**
Only 108 x 30 x 8 mm and 58 g for discreet placement.
- **Up to 128 Devices**
Supports up to 128 Aqara devices when Zigbee routers/repeaters are used.
- **All-Round Compatibility**
Exposes supported Aqara devices to HomeKit, Alexa, Google, IFTTT and more.
- **2.4 GHz Wi-Fi Repeater**
Can extend 2.4 GHz Wi-Fi coverage for a small number of devices.

Note: Full 128-device capacity requires Zigbee routers/repeaters such as neutral wall switches or smart plugs.

Technical Specifications

Brand	Aqara
Product Name	Hub E1
Model	HE1-G01
Color	White
Dimensions	108 x 30 x 8 mm (4.25 x 1.18 x 0.31 in.)
Weight	58 g
Wireless Protocols	Zigbee 3.0 IEEE 802.15.4; Wi-Fi IEEE 802.11 b/g/n 2.4 GHz
Port	USB-A
Input Power	5V DC 0.5A
Total Power Consumption	2.5W Max
Operating Temperature	-10°C to 40°C (14°F to 104°F)
Operating Humidity	0% to 95% RH, no condensation
Box Contents	Hub E1 x 1, User Manual x 1

What is in the Box

- Aqara Hub E1 x 1
- User Manual x 1

Physical Design

USB-A connector with adjustable shaft, front button, LED indicator and compact white body.

Supported Ecosystems

Aqara Home

Apple HomeKit

Amazon Alexa

Google Assistant